

Enforcer ET10

70 Volt 10 Watt Multi-Tap Audio Transformer

The ET10 transformer is a commercial quality 70 or 25 volt transformer that can be used with 8 ohm loads to 10 watts RMS. Dual voltage allows a wide range of applications. The ET10 uses leads for termination to both speaker and amplifier output.



WATTS, RMS:	10
PRIMARY VOLTAGE:	70 / 25V
PRIMARY TAPS IN WATTS -	70V: .31, .62, 1.25, 2.5, 5, 10 25V: .31, .62, 2.5, 5, 10
SECONDARY IMPEDANCE:	8 Ohms
INSERTION LOSS:	1.3dB
FREQUENCY RESPONSE:	60 to 15kHz
MOUNTING HOLES:	2 3/8"