

Rolls MX54s Pro-Mix Plus

The MX54s Pro-Mix Plus mixes three microphones into two transformer balanced outputs. It has three XLR inputs, each with individually switchable phantom power, and Low Cut switches, a Level control, and a Pan control. As mentioned, it has two transformer balanced, XLR outputs. A 1/4 inch Aux/Headphone output has been provided along with a Clip indicator, Power indicator, and Power switch. The unit is also powered by two 9-Volt alkaline batteries or an external 12VDC power source.

